

Yaesu FT1000-MP**Menu Settings**

Func. No.	Function	Setting Range
0-1	MEMORY GROUP 1 CHANNELS	1-99
0-2	MEMORY GROUP 2 CHANNELS	0-99
0-3	MEMORY GROUP 3 CHANNELS	0-99
0-4	MEMORY GROUP 4 CHANNELS	0-99
0-5	MEMORY GROUP 5 CHANNELS	0-99
0-6	QUICK MEMORY CHANNELS	1-5
0-7	NONE	
0-8	V > M AUTO CHANNEL UP	ON / OFF
0-9	NONE	
1-0	VFO A & B DIAL SPEED	x2,x4
1-1	SHUTTLE JOG DIAL SPEED	1- 100ms
1-2	IF SHIFT/WIDTH STEP SIZE	10 / 20Hz
1-3	MAIN VFO-A TUNING STEP SIZE	0.625 - 20 Hz
1-4	SUB VFO-B TUNING STEP SIZE	0.625 - 20 Hz
1-5	CHANNEL STEP SIZE	1 - 100kHz
1-6	QUICK SPLIT OFFSET	1 - 100 kHz(±)
1-7	AUTOMATIC SELECTION OF THE AGC DECAT	ON/OFF
1-8	CLAR M-TUNE FUNCTION	ON/OFF
1-9	CLAR TUNING STEP SIZE	0.625 20 Hz
2-0	SCAN PAUSE	ON/OFF
2-1	SCAN RESUME MODE	CAR STOP/CAR SLOW/CAR TIME
2-2	NONE	
2-3	MEMORY SCAN SPEED (DWELL TIME)	100ms - 1 s
2-4	VFO SCAN SPEED (DWELL TIME)	1 - 100ms
2-5	AUTO MEMORY WRITE	OFF / GROUP 1 / GROUPS ALL
2-6	MEMORY SCAN SKIP	OFF/ALL
2-7	SCAN DELAY TIME	1 - 10s
2-8	NONE	
2-9	IF NOTCH MODE	IF NOTCH / AUTO / SELECT
3-0	FREQUENCY DISPLAY	OFFSET / CARRIER
3-1	DISPLAY RESOLUTION	10 Hz/100 Hz/1 kHz
3-2	ETS (Enhanced Tuning Scale)	CLAR / DIAL
3-3	Transverter Frequency Display	OFF / 50 / 144 / 430
2-4	Dimmer (Display Brightness)	LOW / HI
3-5	Panel Display Mode	PITCH / CLAR / CH FREQ / OFFSET
3-6	SUB VFO-B S-Meter	ON /OFF
3-7	MAIN VFO-A Meter Peak-Hold	ON /OFF
3-8	SUB VFO-B Meter Peak-Hold	ON /OFF
3-9	NONE	
4-0	RF Output Power (limit)	100 / 50 / 10 W
4-1	KEY & PANEL BEEPER	ON /OFF
4-2	KEY & PANEL BEEP PITCH	220 -- 7040 Hz or BEEP TUN ON /OFF
4-3	TUNING DRIVE (AUTO POWER-DOWN)	10 / 50 / 100 W

4-4	TX AUDIO EDSP	OFF,1,2,3,4
	EDSP Filters	
	SSB LPF	100 -- 3200 Hz
	SSB HPF	100 -- 1800Hz
4-5	CW BPF	60 / 120 / 240 Hz
	AM LPF	1000 -- 3200 Hz
	AM HPF	100 18001-jz
	DIGITAL FILTER	PKT / SSTV / FAX
4-6	DVS PX RECORDING	MAIN VFO / SUB VFO
4-7	DVS PTT CONTROL	ON / OFF
4-8	HEADPHONE AUDIO	MONO / STEREO 1 / STEREO2
4-9	AF GAIN BALANCE CONTROL	SEPARATE / BALANCE
5-0	8.2 MHz FILTER	2.4 K ON / OFF
5-1	8.2 MHz FILTER	2.0K ON / OFF
5-2	8-2 MHz FILTER	500 ON / OFF
5-3	8.2 MHz FILTER	250 ON / OFF
5-4	455 KHz FILTER	2.4K ON / OFF
5-5	455 KI-4z FILTER	20 K ON/OFF
5-6	455 KHz FILTER	500 ON / OFF
5-7	455 KHz FILTER	250 ON / OFF
5-8	SUB VFO RX FILTER	ON / OFF
5-9	TX EDSP FILTER	6.0 kHz / 2.0 kHz
6-0	RTTY SHIFT	170 / 425 / 850Hz
6-1	RTTY POLARITY	NORMAL / REVERSE
6-2	RTTY TONE PAIR	HIGH TONE / LOW TONE
6-3	PITY FREQUENCY DISPLAY	CARRIER / OFFSET
6-4	PACKET FREQUENCY DISPLAY OFFSET	±3.000 kHz
6-5	PACKET TONE FREQUENCY	1170 -- 2215 Hz
6-6		
6-7	CTCSS TONE SELECT	67.0 -- 250.3 Hz
6-8	TONE MODE	CONTINUOUS / BURST
6-9	REPEATER SHIFT (TX OFFSET)	0 -- 200 kHz
7-0	ELECTRONIC KEYSER MODE	IAMBIC 1/BUG / IMABIC 2
7-1	KEYER DOT WEIGHTING	0 (0.5 ~ -127 (2.0)
7-2	KEYER DASH WEIGHTING	0 (2.0) ~ 127 (4.5)
7-3	KEYER CONTEST NUMBER	0000-9999
7-4	KEYER BREAK-IN TIME	0 -- 30ms
7-5	KEYER DELAY TIME	0.00 -- 5.10
7-6	CONTEST NO. PLAYBACK STYLE	ID NO.1,2,3,4,5,6,1,8,9 STYLE
		SSB (Rx) 100-3100Hz, 300-2800 Hz, OF
		SSB (Tx) 100-3100Hz, 150-3100 Hz,
7-7	EDSP MODULATION & DEMODULATION	200-3100Hz, 300-3100 Hz, OFF
		CW (Rx) 100-3100Hz,OFF
		AM (Rx) 70-3800hz, OFF
7-8	SUB RECEIVER	ON/OFF
7-9	REMOTE CONTROL FUNCTION	EL / PANEL / AIO / BIO
8-0	FAST KEY OPERATION	CONTINUOUS / TOGGLE
8-1	LOCK SELECTION	DIAL / PANEL / PRIMARY
8-2	SPLIT OPERATION	NORM / AUTO / A-B
8-4	FRONT END RF AMP SELECTION	TUNED / FLAT
8-5	ANT KEY FUNCTION	AUTO/ON/OFF

	USER SETTING	
	MODE	LSB, USB, CW (U&L), RTTY (U&L), PK
	DISPLAY OFFSL1	±5.000 kHz
	RECEIVE PLL	±5.000 kHz
8-6	RECEIVE CARRIER	450.000 ~ 460.000 kHz
	TRANSMIT PLL	±5.000 kHz
	TRANSMIT CARRIER	450.000 ~ 460.000 kHz
	RTTY OFFSET	±5.000 kHz
	EASY SET	OFF/SSTV/FAX
8-7	SUB RXAGC	AUTO / SLOW / FAST
8-8	TUNER	ON/OFF
	CARRIER OFFSET	
	RX LSB CARRIER	0.200 - 0.500 kHz
	TX USB CARRIER	0.200 - 0.500 kHz
	PROC. LSB CARRIER	0.200 - 0.500 kHz
8-9	CARRIER OFFSET	0.200 - 0.500 kHz
	RX LSB CARRIER	0.200 0.500 kbz
	TX USB CARRIER	0.200 - 0.500 kHz
	PROC. USB CARRIER	0.200 - 0.500 kl-4z
	TX AM CARRIER	0.200 -. 0.500 kHz

The following are hidden menus

Turn on the radio with the FAST and the LOCK key pressed at the same time. This should enable the further menu items. Note ..it is FAST and LOCK to enter these menu settings. Afterwards use FAST and ENT as normal

9-0	Collins filter (scrolling menu!!!!)	RX LSB CAR TX LSB CAR PROC LSB RX USB TX USB PROC USB TX A3 PROC A3
9-1	IF Gain amplifier	
9-2	TX IF Gain amplifier (scrolling menu)	T IF-018 T IF-035 T IF-070 T IF-100 T IF-140 T IF-180 T IF-210 T IF-245 T IF-280 T IF-290
9-5	CPU Self check (flashes like a Christmas tree)	cPu - 1.30
9-6	Linear graph indicator	OFF / ON
9-8	Factory date of production	
9-9	Ability to transmit in general coverage	